

P699 – FPGA-based USM™ Main XMC

- Main XMC for USM™ Universal Submodules
- PCIe® 2.5 Gbit/s
- 1 USM™ slot
- 1 FPGA 24 624 LEs (for user-defined I/O)
- 32 MB DDR2 SDRAM
- 4 MB Flash
- -10 to +70°C screened



USM™ Universal Submodules make XMC modules more flexible than ever. The main XMC P699 gets its specific function through the IP cores implemented inside the onboard FPGA. This function can be changed at any time through implementation of different IP cores. The corresponding line drivers are realized on the USM™ which is simply plugged on the P699.


The same USM™ may also be used on PMCs, conduction-cooled PMCs or M-Modules™ supporting the USM™ concept. A new design is then limited to the USM™ module and the FPGA content and therefore saves development time and costs. If local intelligence is needed, a Nios® soft processor can be implemented in the Cyclone® III FPGA on request.

The growing range of Wishbone-based standard IP cores from MEN comprise different UARTs, Ethernet, fieldbus interfaces, graphics, digital I/O etc.

The USM™ concept has been developed for harsh environments. Therefore, the P699 uses robust connectors to the USM™, while all other components are soldered, and operates in a -10 to +70 °C temperature range.

The P699 is an XMC mezzanine card suitable for any compliant host carrier board in any type of bus system, i.e. CPCI, VME or on any type of stand-alone SBC. Compared to PMC, the XMC standard defines a different board-to-board connector for support of PCI Express®. Appropriate carrier cards in 3U, 6U and other formats are available from MEN or other manufacturers.

Diagram



Technical Data

Functionality	■ User-defined through FPGA ■ Line drivers and/or additional hardware implemented on USM™ Universal Submodule (not included)
Memory	■ 32MB SDRAM memory □ Soldered □ DDR2 □ 133MHz memory bus frequency □ FPGA-controlled ■ 4MB non-volatile Flash □ For FPGA configuration data □ FPGA-controlled □ Serial SPI Flash, 33MHz
FPGA	■ Standard factory FPGA configuration: □ Chameleon Table V2 □ PCI Express® interface/PCIe® to Wishbone bridge □ ID EEPROM emulation □ 16Z069_RST - Reset controller □ 16Z052_GIRQ - Interrupt controller □ 16Z001_SMB - SMBus controller □ 16Z126_SERFLASH - Serial Flash interface □ 16Z043_SDRAM - DDR2 SDRAM controller □ 16Z125_UART - UART controller □ 16Z034_GPIO - GPIO controllers (3 IP cores, for onboard LEDs and 16-bit I/O) ■ The FPGA offers the possibility to add customized I/O functionality. See FPGA.
USM™ Slot	■ One slot for a standard USM™ module ■ For implementation of line drivers and/or additional hardware
Miscellaneous	■ Eight front-panel LEDs, FPGA-controlled ■ I²C interface to detect the USM™ module
XMC Characteristics	■ Compliant with XMC standard VITA 42.3-200x ■ PCI Express® links: one x1
PCI Express®	■ One x1 link ■ Data rate 250MB/s in each direction (2.5 Gbit/s per lane)
Peripheral Connections	■ Via front panel on a shielded 50-pin HP D-Sub SCSI 2 receptacle connector
Electrical Specifications	■ Isolation voltage: □ Voltage depends on implementation and signal routing of USM™ ■ Supply voltage/power consumption: □ +5V and +12V (-5%/+5%) □ +3.3V (-5%/+5%) □ Consumption depends on FPGA and USM™ configuration
Mechanical Specifications	■ Dimensions: conforming to IEEE 1386.1 ■ Weight: 70g (w/o USM™ module)
Environmental Specifications	■ Temperature range (operation): □ -10..+70°C (screened) □ Airflow: min. 10m³/h ■ Temperature range (storage): -40..+85°C ■ Relative humidity (operation): max. 95% non-condensing ■ Relative humidity (storage): max. 95% non-condensing ■ Altitude: -300m to + 3,000m ■ Shock: 15g/11ms ■ Bump: 10g/16ms ■ Vibration (sinusoidal): 2g/10..150Hz ■ Conformal coating on request

Technical Data

MTBF	■ 757,662h @ 40°C according to IEC/TR 62380 (RDF 2000)
Safety	■ PCB manufactured with a flammability rating of 94V-0 by UL recognized manufacturers
EMC	■ Conforming to EN 55022 (radio disturbance), IEC1000-4-2 (ESD) and IEC1000-4-4 (burst)
Software Support	■ Flash update tools for Linux, Windows®, VxWorks®, QNX® ■ Driver software depending on implemented FPGA functions ■ UART driver software for Windows® on request ■ For more information on supported operating system versions and drivers see Downloads.

FPGA

This product offers the possibility to add customized I/O functionality in FPGA.

Flexible Configuration	■ Customized I/O functions can be added to the FPGA. ■ It depends on the board type, pin counts and number of logic elements which IP cores make sense and/or can be implemented. Please contact MEN for information on feasibility. ■ You can find more information on our web page "User I/O in FPGA"
FPGA Capabilities	■ FPGA Altera® Cyclone® III EP3C25 □ 24,624 logic elements □ 594 Kbits total RAM □ Supports Nios® II soft processor ■ Connection □ Functions can be linked to Wishbone bus □ Available pin count: 46 pins (FPGA to USM™) □ Functions available via USM™ at front I/O connector ■ Functional updates via software □ MEN offers Flash update tools for different operating systems.

Ordering Information

Standard P699 Models	15P699-00	USM™ main XMC, -10..+70°C screened
Miscellaneous Accessories	05P000-01	25 mounting screw sets to fix PMC/XMC modules on carrier boards
	05P599-00	PMC/M-Module™ cable, 2m, with 50-pin HP D-Sub 50 M both sides, 0..+60°C
	08U500-00	Universal Submodule for prototyping, -40..+85°C qualified
Software: Linux	This product is designed to work under Linux. See below for potentially available separate software packages from MEN.	
	13Z017-06	MDIS5™ low-level driver sources (MEN) for 16Z034_GPIO and 16Z037_GPIO
	13Z025-90	Linux native driver (MEN) for 16Z025_UART, 16Z057_UART and 16Z125_UART
	13Z100-91	Linux FPGA update tool (MEN)
Software: Windows®	This product is designed to work under Windows®. See below for potentially available separate software packages from MEN.	
	13Z017-70	MDIS4™/2004 / MDIS5™ Windows® driver (MEN) for 16Z034_GPIO devices
	13Z100-70	Windows® FPGA update tool (MEN)
Software: VxWorks®	This product is designed to work under VxWorks®. For details regarding supported/unsupported board functions please refer to the corresponding software data sheets.	
	13Z017-06	MDIS5™ low-level driver sources (MEN) for 16Z034_GPIO and 16Z037_GPIO
	13Z025-60	VxWorks® native driver (MEN) for 16Z025_UART, 16Z057_UART and 16Z125_UART
	13Z100-60	VxWorks® FPGA update tool (MEN)
Software: QNX®	This product is designed to work under QNX®. For details regarding supported/unsupported board functions please refer to the corresponding software data sheets.	
	13Z017-06	MDIS5™ low-level driver sources (MEN) for 16Z034_GPIO and 16Z037_GPIO
	13Z100-40	QNX® FPGA update tool (MEN)
For operating systems not mentioned here contact MEN sales .		
Documentation	Compare Chart mezzanine functions on PMC/XMC and PC-MIP® » Download	
	20P699-00	P699 User Manual
	20U500-00	USM™ Specification
	21M199-00	P599/M199 Programmer's Guide

Contact Information

Germany

MEN Mikro Elektronik GmbH
Neuwieder Straße 3-7
90411 Nuremberg
Phone +49-911-99 33 5-0
Fax +49-911-99 33 5-901

info@men.de
www.men.de

France

MEN Mikro Elektronik SA
18, rue René Cassin
ZA de la Châtelaine
74240 Gaillard
Phone +33 (0) 450-955-312
Fax +33 (0) 450-955-211

info@men-france.fr
www.men-france.fr

USA

MEN Micro, Inc.
24 North Main Street
Ambler, PA 19002
Phone (215) 542-9575
Fax (215) 542-9577

sales@menmicro.com
www.menmicro.com

The date of issue stated in this data sheet refers to the Technical Data only. Changes in ordering information given herein do not affect the date of issue. All brand or product names are trademarks or registered trademarks of their respective holders.

MEN is not responsible for the results of any actions taken on the basis of information in the publication, nor for any error in or omission from the publication.

MEN expressly disclaims all and any liability and responsibility to any person, whether a reader of the publication or not, in respect of anything, and of the consequences of anything, done or omitted to be done by any such person in reliance, whether wholly or partially, on the whole or any part of the contents of the publication.

The correct function of MEN products in mission-critical and life-critical applications is limited to the environmental specification given for each product in the technical user manual. The correct function of MEN products under extended environmental conditions is limited to the individual requirement specification and subsequent validation documents for each product for the applicable use case and has to be agreed upon in writing by MEN and the customer. Should the customer purchase or use MEN products for any unintended or unauthorized application, the customer shall indemnify and hold MEN and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim or personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that MEN was negligent regarding the design or manufacture of the part.

In no case is MEN liable for the correct function of the technical installation where MEN products are a part of.

Copyright © 2013 MEN Mikro Elektronik GmbH. All rights reserved.