


A14C – 6U VME64 MPC8540 CPU Board

- **PowerPC® MPC8540 / 800MHz**
- **FPGA 12,000 LEs (approx. 144,000 gates)**
- **1-slot 64-bit VMEbus master and slave**
- **Up to 2 GB (ECC) DRAM**
- **NAND Flash, FRAM**
- **Graphics via PMC or FPGA**
- **2 Gigabit/1 Fast Ethernet**
- **Up to 6 COMs**
- **Parallel ATA for onboard hard disk**
- **Further I/O individually via FPGA**
- **2 PMC slots**
- **MENMON™ BIOS for PowerPC® cards**



The A14C is an advanced PowerPC® based single-board computer for embedded applications. It features full VME64 support and it can be used as a master or a slave in a VMEbus environment. The CPU card provides 1 MB local shared SRAM for slave access and communication between the local CPU and another VMEbus master.


The A14C is controlled by an MPC8540 integrated PowerPC® processor working at 800MHz. The SBC is equipped with a DDR SO-DIMM socket for data storage, with NAND Flash for program storage as well as with non-volatile FRAM. The board provides front-panel access for two Gigabit Ethernet, one fast Ethernet and one COM via four RJ45 connectors. Four more UARTs are optionally accessible via SA-Adapters™ for front connection.

Additional functionality such as graphics, touch, CAN, binary I/O etc. can be realized as IP cores in FPGA for the needs of the individual application. The corresponding PHYs are available via SA-Adapters™ on a transition module to the rear.

The FPGA acts as a standard PCI device on the A14C. The FPGA functions are loaded by software during power-up within less than 1s. FPGA updates can be carried out dynamically during operation.

In addition, the A14C can be equipped with PMC mezzanine cards supporting 64 bits/66 MHz as well as front I/O and rear I/O (PIM). The A14C comes with MENMON™ support. This firmware/BIOS can be used for bootstrapping operating systems (from disk, Flash or network), for hardware testing, or for debugging applications without running any operating system.

Diagram



Technical Data

CPU	■ PowerPC® □ MPC8540 PowerQUICC™ III □ 800MHz (666..833MHz optional) □ e500 PowerPC® core with SPE APU and MMU □ Integrated Northbridge and Southbridge □ High memory bandwidth
Memory	■ 2x32KB L1 data and instruction cache, 256KB L2 cache / SRAM integrated in MPC8540 ■ Up to 2GB SDRAM system memory □ SO-DIMM slot for SDRAM modules □ DDR2100 with or without ECC □ 133MHz memory bus frequency ■ Up to 1GB soldered NAND Flash (and more), FPGA-controlled ■ Up to 16MB additional SDRAM, FPGA-controlled, e.g. for video data and NAND Flash firmware ■ 8MB boot Flash ■ 32KB non-volatile FRAM ■ Serial EEPROM 4kbits for factory settings
Mass Storage	■ Parallel IDE (PATA) □ One port for hard-disk drives □ Drive can be connected via ribbon cable or mounted directly on the CPU board using MEN adapter kit (instead of PMC modules) □ Only one VMEbus slot needed even with hard disk □ PIO mode 0 support ■ Up to 1GB soldered ATA NAND Flash (and more), FPGA-controlled
I/O	■ Three Ethernet channels □ Two 10/100/1000Base-T Ethernet channels □ One 10/100Base-T Ethernet channel □ Three RJ45 connectors at front panel □ Two onboard LEDs to signal LAN Link and Activity ■ One RS232 UART (COM1) □ One RJ45 connector at front panel □ Data rates up to 115.2kbit/s □ 16-byte transmit/receive buffer □ Handshake lines: CTS, RTS ■ One LVTTTL UART (COM10) □ FPGA-controlled □ Accessible via rear I/O □ Data rates up to 115.2kbit/s □ 60-byte transmit/receive buffers □ Handshake lines: CTS, RTS; DCD, DSR, DTR; RI ■ Quad UART (COM20..COM23) □ Physical interface using SA-Adapters™ via 10-pin ribbon cable on I/O connector □ RS232..RS485, isolated or not: for free use in system (e. g. cable to front) □ Data rates up to 115.2kbit/s □ 128-byte transmit/receive buffer □ Handshake lines: CTS, RTS; DCD, DSR, DTR; RI ■ GPIO □ 39 GPIO lines □ FPGA-controlled □ Accessible via rear I/O
Front Connections	■ Three Ethernet (RJ45) ■ COM1 (RJ45) ■ COM20..COM23 (optional, instead of PMC modules, or in second front-panel slot) ■ PMC 0 and 1

Technical Data

Rear I/O	■ COM10 ■ GPIO ■ Mezzanine rear I/O: PMC 0
FPGA	■ Standard factory FPGA configuration: □ Main bus interface □ 16Z070_IDEDISK - IDE controller for NAND Flash □ 16Z043_SDRAM - Additional SDRAM controller (16MB) □ 16Z023_IDENHS - IDE controller (PIO mode 0; non-hot-swap) □ 16Z025_UART - UART controller (controls COM10) □ 16Z034_GPIO - GPIO controller (40 lines, 5 IP cores) ■ The FPGA offers the possibility to add customized I/O functionality. See FPGA.
Mezzanine Slots	■ Two PMC slots □ Compliant with PMC standard IEEE 1386.1 □ Up to 64-bit/64-MHz, 3.3V V(I/O) □ PMC I/O module (PIM) support through J4
Miscellaneous	■ Real-time clock with GoldCap backup ■ Power supervision and watchdog ■ Reset button, GPIO-controlled, in ejector handle
Local PCI Bus	■ 32-bit/33-MHz, 3.3V V(I/O) ■ Compliant with PCI Specification 2.2
VMEbus	■ Compliant with VME64 Specification ■ Slot-1 function with auto-detection ■ Master □ D08(E0):D16:D32:D64:A16:A24:A32:ADO:BLT:RMW ■ Slave □ D08(E0):D16:D32:D64:A16:A24:A32:BLT:RMW ■ 1MB shared fast SRAM ■ DMA ■ Mailbox functionality ■ Interrupter D08(O):I(7-1):ROAK ■ Interrupt handler D08(O):IH(7-1) ■ Single level 3 fair requester ■ Single level 3 arbiter ■ Bus timer ■ Location Monitor ■ Performance □ Coupled read/write D32 non-block transfer rate 6.5 MB/s □ DMA read/write D32 BLT transfer rate 12.1 MB/s □ DMA read/write D64 MBLT transfer rate 25 MB/s
Electrical Specifications	■ Supply voltage/power consumption: □ +5V (-3%/+5%), 3A typ. □ +12V (-5%/+5%), only provided for PMCs that need 12V □ -12V (-5%/+5%), only provided for PMCs that need 12V ■ MTBF: 92,800h @ 40°C (derived from MIL-HDBK-217F)
Mechanical Specifications	■ Dimensions: standard double Eurocard, 233.3mm x 160mm ■ Weight (without PMC modules): 450g

Technical Data

Environmental Specifications	■ Temperature range (operation): □ 0..+60°C □ Airflow: min. 10m³/h ■ Temperature range (storage): -40..+85°C ■ Relative humidity (operation): max. 95% non-condensing ■ Relative humidity (storage): max. 95% non-condensing ■ Altitude: -300m to + 3,000m ■ Shock: 15g/11ms ■ Bump: 10g/16ms ■ Vibration (sinusoidal): 2g/10..150Hz ■ Conformal coating on request
Safety	■ PCB manufactured with a flammability rating of 94V-0 by UL recognized manufacturers
EMC	■ Tested according to EN 55022 (radio disturbance), IEC1000-4-2 (ESD) and IEC1000-4-4 (burst)
BIOS	■ MENMON™
Software Support	■ VxWorks® ■ Linux (ELinOS) ■ QNX® ■ For more information on supported operating system versions and drivers see Downloads.

FPGA

This product offers the possibility to add customized I/O functionality in FPGA.

Flexible Configuration	■ Customized I/O functions can be added to the FPGA. ■ It depends on the board type, pin counts and number of logic elements which IP cores make sense and/or can be implemented. Please contact MEN for information on feasibility. ■ You can find more information on our web page "User I/O in FPGA"
FPGA Capabilities	■ FPGA Altera® Cyclone® EP1C12 □ 12,060 logic elements □ 239,616 total RAM bits ■ Connection □ Available pin count: 47 pins □ Functions available via onboard and rear I/O connectors

Configuration & Options

Standard Configurations

Article No.	CPU Type	Clock	System RAM	NAND Flash	Additional SDRAM	FRAM	Boot Flash	Mezzanine Slots	Operation Temperature
01A014C00	MPC8540	800 MHz	512 MB (no ECC)	128 MB	16 MB	32 KB	8 MB	2 PMC	0..+60°C

Options

CPU	■ Type □ MPC8540 □ MPC8560 ■ Clock □ 666..833 MHz
Memory	■ System RAM □ 256 MB, 512 MB, 1 GB or 2 GB □ With or without ECC ■ NAND Flash □ 0 MB up to maximum available ■ Additional SDRAM □ 0 MB or 16 MB ■ FRAM □ 0 MB or 32 MB ■ Boot Flash □ 8 MB or 16 MB
I/O	■ Quad UART (COM20..23) □ Direct onboard connection via 10-pin connectors, instead of PMCs ■ Front Connections □ D-Sub instead of RJ45 connectors
Mezzanine Slots	■ 2 PMC ■ 3 PC-MIP®
Operation Temperature	■ 0..+60°C

Please note that some of these options may only be available for large volumes. Please ask our sales staff for more information.

Ordering Information

Standard A14C Models	01A014C00	MPC8540/800MHz, 512MB DRAM, 128MB NAND Flash, 16MB graphics memory, 32KB FRAM, 2 PMC slots, 0..+60°C
SA-Adapters™	You can find a more detailed overview of possible carrier board/SA-Adapter™ combinations along with software support in our option matrix (PDF) .	
	05A013-00	Mounting kit for 4 SA-Adapters™ for 6U VME/cPCI boards, incl. 1-slot front panel and ribbon cable, without SA-Adapters™
	08SA01-00	RS232, not optically isolated, 0..+60°C
	08SA02-00	RS422/485, half duplex, optically isolated, 0..+60°C
	08SA02-01	RS422/485, full duplex, optically isolated, 0..+60°C
	08SA02-07	RS422/485, full duplex, optically isolated, -40..+85°C screened
	08SA03-00	RS232, optically isolated, 0..+60°C
	08SA03-01	RS232, optically isolated, -40..+85°C screened
Systems & Card Cages	MEN delivers turn-key systems completely installed (hardware, operating system, accessories), wired and tested. Different rack sizes, power supplies and backplanes on request. For details please contact your local sales representative.	
Miscellaneous Accessories	05F006-00	RS232 interface cable RJ45 to 9-pin D-Sub (1 COM to 1 COM), 2m
	05P000-01	25 mounting screw sets to fix PMC/XMC modules on carrier boards
	08AD71-00	AD71, 2.5" hard disk adapter for A13, A14, A15, D6, D7
Software: Linux	This product is designed to work under Linux. See below for potentially available separate software packages from MEN. This product is designed to work under ELinOS Embedded Linux by Sysgo. For more information and product support please contact www.sysgo.com .	
	13Z014-90	Linux device driver (MEN) for PCI-to-VME bridge on A12, A13, A14, A15, A17, A19, A20 and B11
	13Z017-06	MDIS5™ low-level driver sources (MEN) for 16Z034_GPIO and 16Z037_GPIO
	13Z025-90	Linux native driver (MEN) for 16Z025_UART, 16Z057_UART and 16Z125_UART
	13Z100-91	Linux FPGA update tool (MEN)
Software: VxWorks®	This product is designed to work under VxWorks®. For details regarding supported/unsupported board functions please refer to the corresponding software data sheets.	
	10EM03-60	VxWorks® BSP (MEN) for EM3, EM3A, EM8, EM8A, EK7, A14C and F13
	13P010-60	VxWorks® UART driver (MEN) for P10 and P11
	13Z017-06	MDIS5™ low-level driver sources (MEN) for 16Z034_GPIO and 16Z037_GPIO
	13Z025-60	VxWorks® native driver (MEN) for 16Z025_UART, 16Z057_UART and 16Z125_UART
	13Z100-60	VxWorks® FPGA update tool (MEN)

Ordering Information

Software: QNX®	This product is designed to work under QNX®. For details regarding supported/unsupported board functions please refer to the corresponding software data sheets.	
10EM03-40		QNX® BSP (MEN) for EM3, EM3A, EM8, EM8A, EK7, A14C and F13
13Z017-06		MDIS5™ low-level driver sources (MEN) for 16Z034_GPIO and 16Z037_GPIO
13Z025-40		QNX® 6.3 native driver (MEN) for 16Z025_UART and 16Z125_UART
13Z025-41		QNX® 6.4 native driver (MEN) for 16Z025_UART and 16Z125_UART
13Z025-42		QNX® 6.5 native driver (MEN) for 16Z025_UART and 16Z125_UART
13Z100-40		QNX® FPGA update tool (MEN)

Software: Firmware/BIOS

MENMON™ is MEN's firmware/BIOS for PowerPC® platforms.

14EM03-00 MENMON™ (Firmware) for EM3, EM3A, EM8, EM8A, A14C and F13 (object code)

For operating systems not mentioned here [contact MEN sales](#).

Documentation	Compare Chart 6U VMEbus CPU and I/O cards » Download	
20A014CER		A14C Errata
20A014-00		A14C User Manual
21MENM-00		MENMON™ User Manual
21Z025-90		16Z025_UART and 16Z125_UART under Linux User Manual
22Z025-ER		16Z025_UART Errata

Contact Information

Germany

MEN Mikro Elektronik GmbH
Neuwieder Straße 3-7
90411 Nuremberg
Phone +49-911-99 33 5-0
Fax +49-911-99 33 5-901

info@men.de
www.men.de

France

MEN Mikro Elektronik SA
18, rue René Cassin
ZA de la Châtelaine
74240 Gaillard
Phone +33 (0) 450-955-312
Fax +33 (0) 450-955-211

info@men-france.fr
www.men-france.fr

USA

MEN Micro, Inc.
24 North Main Street
Ambler, PA 19002
Phone (215) 542-9575
Fax (215) 542-9577

sales@menmicro.com
www.menmicro.com

The date of issue stated in this data sheet refers to the Technical Data only. Changes in ordering information given herein do not affect the date of issue. All brand or product names are trademarks or registered trademarks of their respective holders.

MEN is not responsible for the results of any actions taken on the basis of information in the publication, nor for any error in or omission from the publication.

MEN expressly disclaims all and any liability and responsibility to any person, whether a reader of the publication or not, in respect of anything, and of the consequences of anything, done or omitted to be done by any such person in reliance, whether wholly or partially, on the whole or any part of the contents of the publication.

The correct function of MEN products in mission-critical and life-critical applications is limited to the environmental specification given for each product in the technical user manual. The correct function of MEN products under extended environmental conditions is limited to the individual requirement specification and subsequent validation documents for each product for the applicable use case and has to be agreed upon in writing by MEN and the customer. Should the customer purchase or use MEN products for any unintended or unauthorized application, the customer shall indemnify and hold MEN and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim or personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that MEN was negligent regarding the design or manufacture of the part.

In no case is MEN liable for the correct function of the technical installation where MEN products are a part of.

Copyright © 2013 MEN Mikro Elektronik GmbH. All rights reserved.